



GEM6

6 CHANNEL LED WIRELESS CONTROLLER

MAIN FEATURES

- 6 OUTPUT CHANNELS
- MARKET-LEADING 10A PER CHANNEL (MAX 40A TOTAL)
- DMX/LUMEN RADIO CRMX OR LOCAL CONTROL
- DRIVES 12V OR 24V LED STRINGS
- COMPREHENSIVE SHORT CIRCUIT PROTECTION



PRODUCT HIGHLIGHTS

THE GEM6 IS A RUGGED AND COMPACT 6-WAY CONTROLLER FOR FULL-COLOUR LED CONTROL OR 3 CHANNELS OF BI-COLOUR.

The GEM6 has a comprehensive yet intuitive user control achieved through 4 large membrane keys, resilient in demanding

conditions. Silicone bands provide additional bump protection and can be colour-coded to help identify the owner.

Capable of handling the highest power jobs, small enough to be hidden discreetly on set.

SPECIFICATIONS

Maximum Current	10A per Channel	Max Ambient Temp	50°C/122°F
Combined Current	40A Max	Dimming resolution	8-bit or 16-bit
Input Voltage Range	12-24V	Width	114mm/4.5"
Protection	Short Circuit Protected	Depth	72mm/2.8"
Output connectors	Phoenix Compatible	Height	33.5mm/1.3"
Control	Wired or Wireless DMX. Local Control	Weight	300g/10.6oz

CONTACT

POWER GEMS LTD
Unit 1, Fairhills Trade Centre,
Fairhills Road,
Irlam, Manchester M44 6BA.
United Kingdom
Tel +44 (0) 161 776 7030

POWER GEMS CORPORATION
26320 Diamond Pl., Suite 180
Santa Clarita
California 91350
USA
Tel +1 818 376 1800

www.powergems.com