



EB1X400B

BOOSTING 4000W 19" HIGH SPEED ELECTRONIC BALLAST

Mk2

MAIN FEATURES

- OUTPUT POWER CAN BE BOOSTED BY 200% FOR UP TO 30 SECONDS
- 0-10V, 4-20MA OR DMX CONTROL
- POWER FACTOR CORRECTED
- IDEAL FOR HIGH SPEED FILMING



PRODUCT HIGHLIGHTS

A 4000W RACK-MOUNTED ELECTRONIC BALLAST THAT CAN BOOST TO 8000W FOR A SHORT PERIOD, MAKING IT IDEAL FOR HIGH-SPEED FILMING APPLICATIONS WHERE AN INCREASE IN LIGHT IS INTERMITTENTLY REQUIRED.

This ballast uses the Power Gems tried-and-tested modular system, allowing rapid and easy servicing.

Additionally, it features an extensive control interface to ensure compatibility with existing installations and control standards.

SPECIFICATIONS

Max Lamp Power	8000W	Power Factor	>0.98
Output Power Options	8kW, 4kW, 2.5kW	Max Ambient Temperature	50°C/122°F
Output Frequency Options	100Hz or user-specified value	Width	482.5mm/19"
Current Draw	38A @ 230V	Height	132.5mm/5.2" (3U)
DMX Built In	Yes	Length	495mm/19.5" (excl. handles and connectors)
Input Voltage Range	190-265V AC	Weight	18.8kg/41.4lb

CONTACT

POWER GEMS LTD
Unit 1, Fairhills Trade Centre,
Fairhills Road,
Irlam, Manchester M44 6BA.
United Kingdom
Tel +44 (0) 161 776 7030

POWER GEMS CORPORATION
26320 Diamond Pl., Suite 180
Santa Clarita
California 91350
USA
Tel +1 818 376 1800

www.powergems.com